

§ 74.1202

translator for all other classes of commercial stations as well as all non-commercial educational stations it is the predicted 1 mV/m field strength contour. A fill-in FM translator's coverage contour must be contained within the primary station's coverage contour. The protected contour for an FM translator station is its predicted 1 mV/m contour.

(h) *Fill-in area.* The area where the coverage contour of an FM translator or booster station is within the protected contour of the associated primary station (*i.e.*, predicted 0.5 mV/m contour for commercial Class B stations, predicted 0.7 mV/m contour for commercial Class B1 stations, and predicted 1 mV/m contour for all other classes of stations).

(i) *Other area.* The area where the coverage contour of an FM translator station extends beyond the protected contour of the primary station (*i.e.*, predicted 0.5 mV/m contour for commercial Class B stations, predicted 0.7 mV/m contour for commercial Class B1 stations, and predicted 1 mV/m contour for all other classes of stations).

[35 FR 15388, Oct. 2, 1970, as amended at 45 FR 37842, June 5, 1980; 52 FR 31405, Aug. 20, 1987; 55 FR 50693, Dec. 10, 1990]

§ 74.1202 Frequency assignment.

(a) An applicant for a new FM broadcast translator station or for changes in the facilities of an authorized translator station shall endeavor to select a channel on which its operation is not likely to cause interference to the reception of other stations. The application must be specific with regard to the frequency requested. Only one output channel will be assigned to each translator station.

(b) Subject to compliance with all the requirements of this subpart, FM broadcast translators may be authorized to operate on the following FM channels, regardless of whether they are assigned for local use in the FM Table of Allotments (§ 73.202(b) of this chapter):

(1) *Commercial FM translators:* Channels 221-300 as identified in § 73.201 of this chapter.

(2) *Noncommercial FM translators:* Channels 201-300 as identified in § 73.201 of this chapter. Use of reserved chan-

47 CFR Ch. I (10-1-04 Edition)

nels 201-220 is subject to the restrictions specified in § 73.501 of this chapter.

(3) In Alaska, FM translators operating on Channels 201-260 (88.1-99.9 MHz) shall not cause harmful interference to and must accept interference from non-Government fixed operations authorized prior to January 1, 1982.

(c) An FM broadcast booster station will be assigned the channel assigned to its primary station.

[35 FR 15388, Oct. 2, 1970, as amended at 39 FR 12990, Apr. 10, 1974; 47 FR 30068, July 12, 1982; 52 FR 8260, Mar. 17, 1987; 55 FR 50693, Dec. 10, 1990]

§ 74.1203 Interference.

(a) An authorized FM translator or booster station will not be permitted to continue to operate if it causes any actual interference to:

(1) The transmission of any authorized broadcast station; or

(2) The reception of the input signal of any TV translator, TV booster, FM translator or FM booster station; or

(3) The direct reception by the public of the off-the-air signals of any authorized broadcast station including TV Channel 6 stations, Class D (secondary) noncommercial educational FM stations, and previously authorized and operating FM translators and FM booster stations. Interference will be considered to occur whenever reception of a regularly used signal is impaired by the signals radiated by the FM translator or booster station, regardless of the quality of such reception, the strength of the signal so used, or the channel on which the protected signal is transmitted.

(b) If interference cannot be properly eliminated by the application of suitable techniques, operation of the offending FM translator or booster station shall be suspended and shall not be resumed until the interference has been eliminated. Short test transmissions may be made during the period of suspended operation to check the efficacy of remedial measures. If a complainant refuses to permit the FM translator or booster licensee to apply remedial techniques which demonstrably will eliminate the interference