

§ 73.54

a period of 7 days, during which no calibration or adjustment of the instrument, subsequent to the initial calibration, shall be made.

(viii) The effects of modulation of the RF signal shall be separately determined, and shall not be included in establishing values for accuracy and repeatability.

NOTE: In paragraph (b)(1) of this section, the requirement that monitors be capable of operation in the 535-1705 kHz band shall apply only to equipment manufactured after July 1, 1992. Use of a monitor in the 1605-1705 kHz band which is not approved for such operation will be permitted pending the general availability of 535-1705 kHz band monitors if a manufacturer can demonstrate, in the interim, that its monitor performs in accordance with the standards in this section on these 10 channels.

(Secs. 4, 5, 303, 48 Stat., as amended, 1066, 1068, 1082 (47 U.S.C. 154, 155, 303))

[38 FR 1917, Jan. 19, 1973, as amended at 49 FR 3999, Feb. 1, 1984; 49 FR 29069, July 18, 1984; 50 FR 32416, Aug. 12, 1985; 50 FR 47054, Nov. 14, 1985; 51 FR 2707, Jan. 21, 1986; 56 FR 64859, Dec. 12, 1991; 57 FR 43290, Sept. 18, 1992; 60 FR 55480, Nov. 1, 1995; 63 FR 36604, July 7, 1998; 66 FR 20755, Apr. 25, 2001]

§ 73.54 Antenna resistance and reactance measurements.

(a) The resistance of an omnidirectional series fed antenna is measured at either the base of the antenna without intervening coupling or tuning networks, or at the point the transmission line connects to the output terminals of the transmitter. The resistance of a shunt excited antenna may be measured at the point the radio frequency energy is transferred to the feed wire circuit or at the output terminals of the transmitter.

(b) The resistance and reactance of a directional antenna shall be measured at the point of common radiofrequency input to the directional antenna system after the antenna has been finally adjusted for the required radiation pattern.

(c) A letter of notification must be filed with the FCC in Washington, DC, Attention: Audio Division, Media Bureau, when determining power by the direct method pursuant to § 73.51. The letter must specify the antenna or common point resistance at the operating frequency. The following infor-

47 CFR Ch. I (10-1-07 Edition)

mation must also be kept on file at the station:

(1) A full description of the method used to make measurements.

(2) A schematic diagram showing clearly all components of coupling circuits, the point of resistance measurement, the location of the antenna ammeter, connections to and characteristics of all tower lighting isolation circuits, static drains, and any other fixtures connected to and supported by the antenna, including other antennas and associated networks. Any network or circuit component used to dissipate radio frequency power shall be specifically identified, and the impedances of all components which control the level of power dissipation, and the effective input resistance of the network must be indicated.

(d) AM stations using direct reading power meters in accordance with § 73.51, can either submit the information required by paragraph (c) of this section or submit a statement indicating that such a meter is being used. Subsequent station licenses will indicate the use of a direct reading power meter in lieu of the antenna resistance value in such a situation.

[66 FR 20755, Apr. 25, 2001, as amended at 67 FR 13231, Mar. 21, 2002]

§ 73.57 Remote reading antenna and common point ammeters.

Remote reading antenna and common point ammeters may be used without further authority according to the following conditions:

(a) Remote reading antenna or common point ammeters may be provided by:

(1) Inserting second radio frequency current sensing device directly in the antenna circuit with remote leads to the indicating instruments.

(2) Inductive coupling to radio frequency current sensing device for providing direct current to indicating instrument.

(3) Capacity coupling to radio frequency current sensing device for providing direct current to indicating instrument.

(4) Current transformer connected to radio frequency current sensing device for providing direct current to indicating instrument.

(5) Using transmission line current meter at transmitter as remote reading ammeter. See paragraph (c) of this section.

(6) Using the indications of the antenna (phase) monitor, provided that when the monitor is used to obtain remote reading indication of non-directional antenna base current, the monitor calibration can be independently made and maintained for each mode of operation.

(b) Devices used for obtaining remote reading antenna or common point current indications, except antenna monitor coupling elements, shall be located at the same point as, but below (transmitter side) the associated main ammeter.

(c) In the case of shunt-excited antennas, the transmission line current meter at the transmitter may be considered as the remote antenna ammeter provided the transmission line is terminated directly into the excitation circuit feed line, which shall employ series tuning only (no shunt circuits of any type shall be employed) and insofar as practicable, the type and scale of the transmission line meter should be the same as those of the excitation circuit feed line meter (meter in slant wire feed line or equivalent).

(d) Each remote reading ammeter shall be accurate to within 2 percent of the value read on its corresponding regular ammeter.

(e) All remote reading ammeters shall conform with the specifications for regular antenna ammeters.

(f) Meters with arbitrary scale divisions may be used provided that calibration charts or curves are provided at the transmitter control point showing the relationship between the arbitrary scales and the reading of the main meters.

(g) If a malfunction affects the remote reading indicators of the antenna or common point ammeter, the operating power may be determined by a method using alternative procedures as described in § 73.51.

[41 FR 36817, Sept. 1, 1976, as amended at 48 FR 38477, Aug. 24, 1983; 49 FR 49850, Dec. 24, 1984; 50 FR 32416, Aug. 12, 1985; 60 FR 55480, Nov. 1, 1995]

§ 73.58 Indicating instruments.

(a) Each AM broadcast station must be equipped with indicating instruments which conform with the specifications described in § 73.1215 for determining power by the direct and indirect methods, and with such other instruments as are necessary for the proper adjustment, operation, and maintenance of the transmitting system. However, auxiliary transmitters with a nominal power rating of 100 watts or less are not required to be equipped with instruments to determine power by the indirect method provided that the licensee can determine the antenna input power at all times.

(b) Since it is usually impractical to measure the actual antenna current of a shunt excited antenna system, the current measured at the input of the excitation circuit feed line is accepted as the antenna current.

(c) The function of each instrument shall be clearly and permanently shown on the instrument itself or on the panel immediately adjacent thereto.

(d) In the event that any one of these indicating instruments becomes defective when no substitute which conforms with the required specifications is available, the station may be operated without the defective instrument pending its repair or replacement for a period not in excess of 60 days without further authority of the Commission. If the defective instrument is the antenna current meter of a nondirectional station which does not employ a remote antenna ammeter, or if the defective instrument is the common point meter of a station which employs a directional antenna and does not employ a remote common point meter, the operating power shall be determined by a method described in § 73.51(a)(1) or § 73.51(d) during the entire time the station is operated without the antenna current meter or common point meter. However, if a remote meter is employed and the antenna current ammeter or common point meter becomes defective, the remote meter can be used to determine operating power pending the return to service of the regular meter.