

**§ 761.207 The manifest—general requirements.**

(a) A generator who relinquishes control over PCB wastes by transporting, or offering for transport by his own vehicle or by a vehicle owned by another person, PCB waste for commercial off-site storage or off-site disposal shall prepare a manifest on EPA Form 8700-22, and if necessary, a continuation sheet. The generator shall specify:

(1) For each bulk load of PCBs, the identity of the PCB waste, the earliest date of removal from service for disposal, and the weight in kilograms of the PCB waste.

(2) For each PCB Article Container or PCB Container, the unique identifying number, type of PCB waste (*e.g.*, soil, debris, small capacitors), earliest date of removal from service for disposal, and weight in kilograms of the PCB waste contained.

(3) For each PCB Article not in a PCB Container or PCB Article Container, the serial number if available, or other identification if there is no serial number, the date of removal from service for disposal, and weight in kilograms of the PCB waste in each PCB Article.

(b) EPA does not maintain supplies of printed copies of Form 8700-22 for public use, although printed copies of the manifest may be available from State offices. Camera-ready copies of the form are available for printing purposes from State offices, EPA Regional Offices, and EPA Headquarters.

(c) If the State to which the shipment is manifested (*i.e.*, consignment State) supplies the manifest and requires its use, then the generator must use that manifest.

(d) If the consignment State does not supply the manifest, but the State in which the generator is located (*i.e.*, generator State) supplies the manifest and requires its use, then the generator must use that State's manifest.

(e) If both the consignment State and the generator State supply manifests and require their use, the generator must use the consignment State's manifest.

(f) If neither the generator State nor the consignment State supplies the manifest, the generator may obtain the manifest from any source.

(g) A generator shall designate on the manifest one off-site commercial storage or disposal facility approved under this part for the commercial storage or disposal of the PCBs and PCB Items described on the manifest.

(h) If the transporter is unable to deliver the PCB waste to the designated disposer or commercial storer, the transporter must contact the generator of the PCB waste for instructions. The generator shall either designate another approved disposer or commercial storer, or instruct the transporter to return the PCB waste back to the generator.

(i) The manifest which accompanies the PCB waste shall consist of at a minimum the number of copies required to provide the generator, the initial transporter, each subsequent transporter, and the owner or operator of the designated commercial storage or disposal facility with one legible copy each for their records, and one additional copy to be returned to the generator by the owner or operator of the first designated commercial storage or disposal facility.

(j) The requirements of this section apply only to PCB wastes as defined in § 761.3. This includes PCB wastes with PCB concentrations below 50 ppm where the PCB concentration below 50 ppm was the result of dilution; these PCB wastes are required under § 761.1(b) to be managed as if they contained PCB concentrations of 50 ppm and above. An example of such a PCB waste is spill cleanup material containing <50 ppm PCBs when the spill involved material containing PCBs at a concentration of ≥50 ppm. However, there is no manifest requirement for material currently below 50 ppm which derives from pre-April 18, 1978, spills of any concentration, pre-July 2, 1979, spills of < 500 ppm PCBs, or materials decontaminated in accordance with § 761.79.

[54 FR 52752, Dec. 21, 1989, as amended at 63 FR 35461, June 29, 1998]

**§ 761.208 Use of the manifest.**

(a)(1) The generator of PCB waste shall:

(i) Sign the manifest certification by hand.