

§ 761.35

40 CFR Ch. I (7-1-05 Edition)

EDITORIAL NOTE: For FEDERAL REGISTER citations affecting § 761.30 see the List of CFR Sections Affected, which appears in the Finding Aids section of the printed volume and on GPO Access.

§ 761.35 Storage for reuse.

(a) The owner or operator of a PCB Article may store it for reuse in an area which is not designed, constructed, and operated in compliance with § 761.65(b), for no more than 5 years after the date the Article was originally removed from use (e.g., disconnected electrical equipment) or 5 years after August 28, 1998, whichever is later, if the owner or operator complies with the following conditions:

(1) Follows all use requirements at § 761.30 and marking requirements at subpart C of this part that are applicable to the PCB Article.

(2) Maintains records starting at the time the PCB Article is removed from use or August 28, 1998. The records must indicate:

(i) The date the PCB Article was removed from use or August 28, 1998, if the removal date is not known.

(ii) The projected location and the future use of the PCB Article.

(iii) If applicable, the date the PCB Article is scheduled for repair or servicing.

(b) The owner or operator of a PCB Article may store it for reuse in an area that does not comply with § 761.65(b) for a period longer than 5 years, provided that the owner or operator has received written approval from the EPA Regional Administrator for the Region in which the PCB Article is stored. An owner or operator of a PCB Article seeking approval to extend the 5-year period must submit a request for extension to the EPA Regional Administrator at least 6 months before the 5-year storage for reuse period expires and must include an item-by-item justification for the desired extension. The EPA Regional Administrator may include any conditions to such approval deemed necessary to protect health or the environment. The owner or operator of the PCB Article being stored for reuse must comply with the other applicable provisions of this part, including the record retention requirements at § 761.180(a).

(c) Any person may store a PCB Article for reuse indefinitely in:

(1) A unit in compliance with § 761.65(b).

(2) A unit permitted under section 3004 of RCRA to manage hazardous wastes in containers.

(3) A unit permitted by a State authorized under section 3006 of RCRA to manage hazardous waste.

[63 FR 35443, June 29, 1998]

Subpart C—Marking of PCBs and PCB Items

§ 761.40 Marking requirements.

(a) Each of the following items in existence on or after July 1, 1978 shall be marked as illustrated in Figure 1 in § 761.45(a): The mark illustrated in Figure 1 is referred to as M₁ throughout this subpart.

(1) PCB Containers;

(2) PCB Transformers at the time of manufacture, at the time of distribution in commerce if not already marked, and at the time of removal from use if not already marked. [Marking of PCB-Contaminated Electrical Equipment is not required];

(3) PCB Large High Voltage Capacitors at the time of manufacture, at the time of distribution in commerce if not already marked, and at the time of removal from use if not already marked;

(4) Equipment containing a PCB Transformer or a PCB Large High Voltage Capacitor at the time of manufacture, at the time of distribution in commerce if not already marked, and at the time of removal of the equipment from use if not already marked;

(5) PCB Large Low Voltage Capacitors at the time of removal from use (see also paragraph (k) of this section).

(6) Electric motors using PCB coolants (See also paragraph (e) of this section).

(7) Hydraulic systems using PCB hydraulic fluid (See also paragraph (e) of this section);

(8) Heat transfer systems (other than PCB Transformers) using PCBs (See also paragraph (e) of this section);

(9) PCB Article Containers containing articles or equipment that must be marked under paragraphs (a) (1) through (8) of this section;